



## Specifications Osram LED Tube T9 SubstiTUBE Circular (EM/Mains) 20W 2200lm - 865 Daylight | Replaces 32W

[View Product](#)

### General Information

|                          |                                      |
|--------------------------|--------------------------------------|
| SKU                      | 242614                               |
| EAN                      | 4058075604698                        |
| Brand                    | Osram                                |
| Manufacturer Name        | LEDTUBE T9C EM 32 20W 865 G10Q OSRAM |
| Full box quantity        | 10                                   |
| Any Lamp all-in warranty | 3 Years                              |
| Energy efficiency class  | E                                    |
| Average Lifetime (h)     | 30000                                |
| Voltage (V)              | 220-240                              |

### Technical Information

|                             |               |
|-----------------------------|---------------|
| Technology                  | LED           |
| Replaces (Watt)             | 32            |
| Wattage                     | 20            |
| Dimmable                    | Not Dimmable  |
| Cap / Base                  | G10q (4-Pins) |
| Rotatable                   | No            |
| Colour Code                 | 865 Daylight  |
| Colour temperature (Kelvin) | 6500 Daylight |
| Colour Rendering (Ra)       | 80-89         |

|                          |                      |
|--------------------------|----------------------|
| Colour of Light          | White                |
| Light colour options     | Single Color         |
| Luminous Flux (Lumen)    | 2200                 |
| Luminous Efficacy (lm/W) | 110                  |
| Product Type Category    | LED T9 Circular Tube |
| Type of sensor           | No Sensor            |

## Lamp Information

|                       |                                                                       |
|-----------------------|-----------------------------------------------------------------------|
| LED Starter included  | Yes                                                                   |
| Ballast for LED Tubes | Conventional – there is a starter, Mains – Directly connected to 230V |
| Series                | Substitute                                                            |

## Dimensions

|               |     |
|---------------|-----|
| Diameter (mm) | 300 |
|---------------|-----|

## Why Any-lamp?



Order from the **largest lighting specialist** in Europe



**Customised** quotation



Up to **7 years warranty**



**Easy** return process

